

# TECH SPEC

## Peragos Tube

## Models

|                           | Peragos Wand 40C   | Peragos Tube 60C  | Peragos Tube 120C   | Peragos Tube 60C Pixel  | Peragos Tube 120C Pixel   |
|---------------------------|--|---|---|---|---|
|                           |   |  |  |  |  |
| Max Power Consumption     | 25W  | 40W   | 80W   | 40W   | 80W   |
| Pixels                    | 1  | 1   | 1   | 16 Pixel  | 32 Pixel  |
| Aperture Length           | 45cm   | 62cm  | 120cm   | 62cm  | 120cm   |
| Light Aperture Angle      | 220°   |   |   |   |   |
| IP Rating                 | IP66 Weather Proof   |   |   |   |   |
| Exchangeable Battery      | ✓  |   |   |   |   |
| Light Engine              | Rayzr Light Engine   |   |   |   |   |
| White Light Mode          | 2,800K-13,000K<br>CRI 94-98 (96±2); TLCI 92-94 (93±1)  |   |   |   |   |
| Ext. CCT Mode             | 1,500K-30,000K   |   |   |   |   |
| G/M Correction            | ✓  |   |   |   |   |
| Digital Gel Library       | Gel Library with 300+ Widely Used Digital Filters  |   |   |   |   |
| HSI Color Mode            | ✓  |   |   |   |   |
| RGBW Color Mode           | ✓  |   |   |   |   |
| x,y Coordinates           | ✓  |   |   |   |   |
| Special Effects           | ✓  |   |   |   |   |
| User-recalibratable       | ✓  |   |   |   |   |
| User Firmware Upgradeable | ✓  |   |   |   |   |
| Wireless Control          | Built-in Wireless Receiver Comaptible To RTXtec Ecosystem with Art-Net<br>* RTX1 router needed for App control or Wifi remote. |   |   |   |   |